



**Australian Designed!**

\*mobile phone not included

## 8 Zone Alarm Panel & LCD Keypad with Telephone Dialer & SMS Messaging Function

The SMS8 is our premiere 8 Zone Alarm Panel and LCD Keypad, ideal for use in a home or business. The system is designed to provide personal security monitoring via your mobile phone using SMS Messaging or optional high security 24 Hour back-to-base monitoring. (\*Fees Apply)

System reports are sent using the industry standard Contact ID communication protocol. The benefit of using the SMS8 to send these reports is that no SIM card is required - SMS messages are sent via your landline.

The SMS dialer function can be disabled if desired so as to operate as a regular 'dialer' alarm control panel only. The system is designed to be easily programmed, with all programming and setup done via a simple menu-driven system.

### Features:

- 8 Hardwired Zones
- One button "Quick Arming" plus "Home Arming" for arming only certain areas - ie: at night you can have the sensors in living areas armed, but those in the bedrooms disarmed.
- Panic, medical and fire emergency buttons
- Key-switch input
- On board modem with Contact ID protocol for optional back-to-base monitoring
- Supports SMS text messaging of alarm information to two separate mobile phone numbers
- Telephone line fault monitoring

### Specifications:

Number of Zones	8 Fully Programmable hardwired zones, including 3 keypad activated EMERGENCY soft zones	Alpha Keypad	User friendly; Menu Driven; Attractive low profile LCD keypad; Add up to 4 keypads
Circuit Type	End of Line Monitoring	Telephone Dialer	Inbuilt
Control Timing	Entry/Exit delay, Siren Time, AC Fail, Phone Line Fail	Digital Communication	Two 16 Digit Phone Numbers
Installer Code	6 Digit; required for all programming	External Output	9.5-14VDC @ 1.5Amps
User Codes	16 (4 Digit) user codes; programmable by master code (user #1)	Outputs	Siren Output - 700mA; Strobe Output - 700mA; Aux. Output - 700mA; Switch Aux Output - 200mA; All electronic fused.
Message Formats	Ademco Contact ID (CID), SMS	Reporting	Dual, split or Back-up
Power Input	16.5VAC	Cabinet Dimensions	Zinc plated CRS 0.8mm steel; 255 x 230 x 67mm (HxWxD)
Standby Battery	12V, 7AH Sealed Lead Acid Battery		

**kit**  
SMS8KITHW

## Professional Hardwired Alarm Kit for COMPLETE Home or Office Protection

If you're after a complete Home or Office alarm system, you **NEED** our SMS8KITHW. It contains a premiere Watchguard™ 8 Zone alarm panel, internal and external sirens, motion sensors, reed switches and an emergency panic button. These detectors and sirens help protect **ALL** areas of your house by performing functions such as monitoring your rooms for movement, and detecting when door or windows are opened. This gives you greater peace of mind that your home is secure against thieves, burglars and vandals.



1 x SMS8 Alarm Control Panel with LCD Keypad



1 x Outdoor Siren/ Strobe



3 x High Quality PIR Sensors



1 x Indoor "Top Hat" Piezo Siren



4 x Surface Reed Switches for Doors or Windows



1 x Emergency Panic Button



1 x 7Ah Sealed Lead Acid Backup Battery  
1 x 16VAC Power Supply  
1 x 100m of 4 Core Alarm Cable

Website: [www.rhino.com.au](http://www.rhino.com.au) Email: [sales@rhino.com.au](mailto:sales@rhino.com.au)

Head Office (Mon - Fri: 8:30am - 5pm): 9 Hannabus Place, McGraths Hill, NSW 2756 Australia Tel: (02) 4577 4708 Fax: (02) 4577 4885

Haberfield Branch  
Mon - Fri: 8:30am - 5pm, Sat: 9-1pm  
223 Ramsay Street, Haberfield,

NSW 2045, Australia  
Tel: (02) 9716 0444 Fax: (02) 9799 2024

Villawood Branch  
Mon - Fri: 8:30am - 5pm, Sat: 9-1pm  
71 Middleton Road, Villawood,

NSW 2163, Australia  
Tel: (02) 9743 8222 Fax: (02) 9743 8590

Wollongong Branch  
(Mon - Fri: 9 - 5pm)

85 Princes Hwy, Fairy Meadow  
NSW 2519, Australia  
Tel: (02) 4228 8737 Fax: (02) 24228 8736