## ---- Watchguard -----

#### **DVR4ENT6**

### Watchguard 4 Channel H.264 Network DVR with Push Video Notification

The Watchguard DVR4ENT6 features Push Video Notifications, with an alarm sensor connected to the DVR, it can send Push Video to your iPad, iPhone and Android mobile device for instant event notification. The DVR4ENT6 is one of our Real-Time 4 Channel H.264 Network DVRs, and it is the ideal product for use in a home or small business, when the owner is after a high quality digital video recorder with entry level functions.

The DVR utilises H.264 video compression technology, which allowing the system to record full D1 resolution images without increasing the resulting file size. This maximises the amount of footage which can be stored on the internal hard drive. Installation and setup of the DVR couldn't be easier thanks to the "Plug and Play" setup and user friendly On-Screen Menu.

The OSD can be easily navigated using the included USB mouse, the DVR Front Panel or operated wirelessly by using the included IR remote control. Recorded video footage and images can be viewed and played back on the DVR. When you need to retrieve the video footage from the DVR, simply use the OSD to backup the footage to a USB Flash Drive via the external USB port, or backup the footage to a remote PC via a network.

### **Model Features:**

- Push Video Notification
- USB Mouse Control with GUI OSD
- Intelligent Motion Recording
- H.264 Video Compression Technology
- Remote / Mobile Surveillance
- Live, Record, Playback, Backup and Network operation at the same time
- USB and network backup



# Watchguard 4 Channel H.264 Network DVR



	DVR4ENT6
Video Compression Format	H.264
Video Input	4 Channels
Audio Input / Output	4 audio inputs, 1 audio output (mono)
Recording Resolutions	704×576 (D1) / 704×288 / 352×288
Recording Framerate	100 fps
Hard Disk Storage	Accommodates 1 SATA HDD (capacity up to 2TB)
Quick Search	Time/Motion/Alarm search mode
Recording Mode	Manual/Timer/Motion/Alarm/Remote
Multiplex Operation	Live display/Record/Playback/Backup/Network operations
SATA Interface	Built-in
USB Mouse Control	YES
Motion Detection Area	16 × 12 grids per channel
Motion Detection Sensitivity	3 adjustable parameters for accurate detection
Pre-alarm Recording	YES
Backup Device	USB 2.0 flash drive / Network
Ethernet	10/100 Base-T. Supports remote control and live view via Ethernet
Web Interface	Licensed software "Video Viewer" / Internet Explorer, Mozilla Firefox, Safari, Opera or
	Google Chrome web browser / QuickTime player
	Web Interface (5 users access simultaneously)
	*Operating System: Windows 7 / Vista / XP / 2000
Network Protocol	TCP/IP, PPPOE, DHCP and DDNS
Event Notification	Push Video, FTP & E-Mail
Push Video	iPhone, iPad and Android
Mobile Surveillance	Yes: iPad, iPhone, Blackberry, Windows Mobile & Java
Picture Zoom	2X digital zoom
PTZ Control	YES
Alarm I/O	4 inputs (1 input for Push Video), 1 output
Key Lock (Password Protection)	YES
Video Loss Detection	YES
Video Adjustable	Hue / Saturation / Contrast / Brightness
Power	DC 19V
Operating Temperature	10°C ~ 40°C
Dimensions (mm)	343(W) x 59(H) x 223(D)
System Recovery	System auto recovery after power failure



Website: www.rhino.com.au Email: sales@rhino.com.au

McGraths Hill Branch Mon - Fri: 8:30am - 5pm 9 Hannabus Place, McGraths Hill NSW 2756, Australia Tel: (02) 4577 4708 Fax: (02) 4577 4885 Haberfield Branch Mon - Fri: 9am - 5pm, Sat: 9-1pm 223 Ramsay Street, Haberfield, NSW 2045, Australia

Tel: (02) 9716 0444 Fax: (02) 9799 2024

Villawood Branch

Mon - Fri: 9am - 5pm, Sat: 9-1pm 71 Middleton Road, Villawood, NSW 2163, Australia Tel: (02) 9743 8222 Fax: (02) 9743 8590